

Datamate J-Tek Connectors

Spare Female Crimp Contacts

❖ Barrel Crimp Contacts are supplied with the connectors - see previous page. Use the order code for extra spare crimps.



DATAMATE J-TEK

CRIMP CONTACTS	WIRE STRIPPING DETAILS												
<p>Large Bore (22 AWG)</p> <p>Small Bore (24 to 28 AWG)</p> <p>Extra Small Bore (28 to 32 AWG)</p>													
	TOOLS												
	<p>Recommended Crimp Tool - M22520/2-01 Positioner - T5747 Contact Insertion/Removal Tool - Z80-280</p> <p>❖ Pre-cabled contacts shown on following page. ❖ Instruction sheets available at www.harwin.com/instructions.</p>												
HOW TO ORDER													
<p>M80 - 0XX 00 XX</p>													
<p>SERIES CODE</p> <table border="1" style="width: 100%;"> <thead> <tr> <th colspan="2" style="background-color: #f4a460;">TYPE</th> </tr> </thead> <tbody> <tr> <td style="text-align: center;">011</td> <td>Large Bore (22 AWG)</td> </tr> <tr> <td style="text-align: center;">013</td> <td>Small Bore (24-28 AWG)</td> </tr> <tr> <td style="text-align: center;">019</td> <td>Extra Small Bore (28-32 AWG)</td> </tr> </tbody> </table>	TYPE		011	Large Bore (22 AWG)	013	Small Bore (24-28 AWG)	019	Extra Small Bore (28-32 AWG)	<p>FINISH</p> <table border="1" style="width: 100%;"> <tbody> <tr> <td style="text-align: center;">01</td> <td>Gold + Tin</td> </tr> <tr> <td style="text-align: center;">05</td> <td>Gold</td> </tr> </tbody> </table>	01	Gold + Tin	05	Gold
TYPE													
011	Large Bore (22 AWG)												
013	Small Bore (24-28 AWG)												
019	Extra Small Bore (28-32 AWG)												
01	Gold + Tin												
05	Gold												

All dimensions in mm.